

## Ersatzteilliste - Bill of Materials

112755 PM 2600 230V POWER-AMP	
Pos. Nr.	Best. Nr.
Ref. No.	Part No.
Bezeichnung	Description

Zubehör	Accessories & packing material
---------	--------------------------------

349832	R-HAL.LI.L24/1600 RACKHALTE	rack ear left
349833	R-HAL.RE.L24/1600 RACKHALTE	rack ear right
356485	BEDIENUNGSANL. PM 2600	owner's manual
335589	FUSS-GUMMI SJ 5009 SW	rubber foot
353475	KRT. SP 5 605X570X314	carton outer
353476	KRT. IN SP 5 485X460X199	carton inner
303715	STYROPOR-ECK 150X150X150X50	styrofoam #2
348018	SCHUTZFOLIE 1200X800X0,05	poly bag
327495	STYROPOR-ECK 150X150X100X50	styrofoam #1
349988	FALTEINLAGE 750X280	carton filler #1
353477	FALTEINLAGE 776X405	carton filler #2

Mechanische Teile	Cabinet material
-------------------	------------------

B0010	341343	BUCHSE-SPEAKON-VIERECK 4POL	speaker socket 4-pole
C0010	333014	KO-SO 0.10MF 275V 20% L	safety cap 100nF/275V
G0010	343270	GLRI GBPC 3504	rectifier GBPC-P 3504
S0010	346720	SCHALTER-NETZ ESB-99888V	power switch
	347348	DK 22 SW/GA C 6FL	rotary knob black
	341382	KNOPF-TASTE 20X8 SW 3.3	push button black
	347347	DK 16 SW/SI C 6FL	knob rotary
	353478	DK 16 SW/SI A1 6FL	knob rotary
	349725	KABEL-NETZ BEARB.AUS 348800	power cord Europe
	353268	KABEL-KONFEKT 8POL 0.420M	ribbon cable assy 8-way
	353031	KABEL-KONFEKT 20POL 0.080M	ribbon cable assy 20-way
	353474	KABEL-KONFEKT 4POL 0.220M	ribbon cable assy 4-way
	351237	KABEL-KONFEKT 6POL 0.150M	ribbon cable assy 6-way
	353192	GRIFF 153 MM ANTHR. 4HE	handle 153mm
	348415	LÜFTER TYP FBA08A24H DC	fan dc 24V
	356325	FB.PM 2600 BED	front panel PM2600
	356326	RW.PM 2600 BED	rear panel PM2600
	353308	DEC.XA2600/PM2600 BEM	top cover
	351876	NT-RG.XA2600/PM2600 LO 230V	mains transformer 230V LO
	348341	FEDERLEISTE 3POL CE100-	connector female 3-pole
	348309	WI-SO PTC K155 100GRAD	resistor ptc
	348341	FEDERLEISTE 3POL CE100-	connector female 3-pole
	351877	NT-RG.XA2600/PM2600 HI 230V	mains transformer 230V HI
	348341	FEDERLEISTE 3POL CE100-	connector female 3-pole
	348805	WI-SO PTC K155 100GRAD	safety component PTC
	348341	FEDERLEISTE 3POL CE100-	connector female 3-pole
	348341	FEDERLEISTE 3POL CE100-	connector female 3-pole

Printplatten, bestückt	PCB sub assemblies
------------------------	--------------------

841668	PCB+A#XA2600/SP3/5/7	PCB assy 84166
--------	----------------------	----------------

CNOTA	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
-------	--------	--------------------	------------------------

112755		PM 2600 230V POWER-AMP		
Pos. Nr.	Best. Nr.			Description
Ref. No.	Part No.	Bezeichnung		
CNOTB	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CNSER	306446	FEDERLEISTE 2,5MM O 9POL		connector female 9-pole
CN002	344862	MESSERLST. 8POL		connector male 8-pin
C0001	351994	KO-KER	120.0PF 500V 2%	cap ceramic 120pF
C0002	351994	KO-KER	120.0PF 500V 2%	cap ceramic 120pF
C0003	301458	KO-EL	2.200MF 63V	cap electrolytic 2.2uF/63V
C0101	351994	KO-KER	120.0PF 500V 2%	cap ceramic 120pF
C0102	351994	KO-KER	120.0PF 500V 2%	cap ceramic 120pF
C0103	301458	KO-EL	2.200MF 63V	cap electrolytic 2.2uF/63V
D0001	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0002	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0003	307916	DIODZ BZX 55C	7V5 0.50W	diode zener 7V5
D0004	307916	DIODZ BZX 55C	7V5 0.50W	diode zener 7V5
D0005	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0006	328769	DIODE MR 752		diode MR 752
D0007	328769	DIODE MR 752		diode MR 752
D0008	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0101	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0102	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0103	307916	DIODZ BZX 55C	7V5 0.50W	diode zener 7V5
D0104	307916	DIODZ BZX 55C	7V5 0.50W	diode zener 7V5
D0105	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0106	328769	DIODE MR 752		diode MR 752
D0107	328769	DIODE MR 752		diode MR 752
D0108	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
Q0001	348409	TRANS 2SC 4793		transistor 2SC 4793
Q0002	351981	TRANS MJL 3281 A		transistor MJL 3281 A
Q0003	331657	TRANS MJ 15022		transistor MJ 15022
Q0004	331657	TRANS MJ 15022		transistor MJ 15022
Q0005	331657	TRANS MJ 15022		transistor MJ 15022
Q0006	331657	TRANS MJ 15022		transistor MJ 15022
Q0007	331657	TRANS MJ 15022		transistor MJ 15022
Q0008	331657	TRANS MJ 15022		transistor MJ 15022
Q0009	348408	TRANS 2SA 1837		transistor 2SA 1837
Q0010	351982	TRANS MJL 1302 A		transistor MJL 1302 A
Q0011	331658	TRANS MJ 15023		transistor MJ 15023
Q0012	331658	TRANS MJ 15023		transistor MJ 15023
Q0013	331658	TRANS MJ 15023		transistor MJ 15023
Q0014	331658	TRANS MJ 15023		transistor MJ 15023
Q0015	331658	TRANS MJ 15023		transistor MJ 15023
Q0016	331658	TRANS MJ 15023		transistor MJ 15023
Q0017	348409	TRANS 2SC 4793		transistor 2SC 4793
Q0018	348421	TRANS 2N 3906		transistor 2N 3906
Q0019	335763	TRANS 2N 3904		transistor 2N 3904
Q0020	348421	TRANS 2N 3906		transistor 2N 3906
Q0021	335763	TRANS 2N 3904		transistor 2N 3904
Q0022	348422	TRANS MPSA 42		transistor MPSA 42
Q0023	348423	TRANS MPSA 92		transistor MPSA 92
Q0024	348423	TRANS MPSA 92		transistor MPSA 92
Q0025	348423	TRANS MPSA 92		transistor MPSA 92
Q0026	348423	TRANS MPSA 92		transistor MPSA 92
Q0027	348422	TRANS MPSA 42		transistor MPSA 42

112755		PM 2600 230V POWER-AMP	
Pos. Nr.	Best. Nr.	Bezeichnung	Description
Ref. No.	Part No.		
Q0028	307911	TRANS BF 393	transistor BF 391
Q0029	307911	TRANS BF 393	transistor BF 391
Q0101	348409	TRANS 2SC 4793	transistor 2SC 4793
Q0102	351981	TRANS MJL 3281 A	transistor MJL 3281 A
Q0103	331657	TRANS MJ 15022	transistor MJ 15022
Q0104	331657	TRANS MJ 15022	transistor MJ 15022
Q0105	331657	TRANS MJ 15022	transistor MJ 15022
Q0106	331657	TRANS MJ 15022	transistor MJ 15022
Q0107	331657	TRANS MJ 15022	transistor MJ 15022
Q0108	331657	TRANS MJ 15022	transistor MJ 15022
Q0109	348408	TRANS 2SA 1837	transistor 2SA 1837
Q0110	351982	TRANS MJL 1302 A	transistor MJL 1302 A
Q0111	331658	TRANS MJ 15023	transistor MJ 15023
Q0112	331658	TRANS MJ 15023	transistor MJ 15023
Q0113	331658	TRANS MJ 15023	transistor MJ 15023
Q0114	331658	TRANS MJ 15023	transistor MJ 15023
Q0115	331658	TRANS MJ 15023	transistor MJ 15023
Q0116	331658	TRANS MJ 15023	transistor MJ 15023
Q0117	348409	TRANS 2SC 4793	transistor 2SC 4793
Q0118	348421	TRANS 2N 3906	transistor 2N 3906
Q0119	335763	TRANS 2N 3904	transistor 2N 3904
Q0120	348421	TRANS 2N 3906	transistor 2N 3906
Q0121	335763	TRANS 2N 3904	transistor 2N 3904
Q0122	348422	TRANS MPSA 42	transistor MPSA 42
Q0123	348423	TRANS MPSA 92	transistor MPSA 92
Q0124	348423	TRANS MPSA 92	transistor MPSA 92
Q0125	348423	TRANS MPSA 92	transistor MPSA 92
Q0126	348423	TRANS MPSA 92	transistor MPSA 92
Q0127	348422	TRANS MPSA 42	transistor MPSA 42
Q0128	307911	TRANS BF 393	transistor BF 391
Q0129	307911	TRANS BF 393	transistor BF 391
R0010	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0011	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0012	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0013	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0014	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0015	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0042	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0047	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0063	348490	WI-SO NTC K 164/100K/J	safety component NTC
R0068	348490	WI-SO NTC K 164/100K/J	safety component NTC
R0110	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0111	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0112	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0113	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0114	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0115	348906	WI-DR 2X 0.33 OHM 7.00W 5%	resistor 2x0.33 Ohm 7watt
R0142	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0147	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0163	348490	WI-SO NTC K 164/100K/J	safety component NTC
R0168	348490	WI-SO NTC K 164/100K/J	safety component NTC
VR001	348675	WI-TRI 2.50 KOHM LIN	pot trim 2.5k Ohm lin

112755		PM 2600 230V POWER-AMP		
Pos. Nr.	Best. Nr.			
Ref. No.	Part No.	Bezeichnung	Description	
VR101	348675	WI-TRI 2.50 KOHM LIN	pot trim 2.5k Ohm lin	

862278	PCBAR#XA2600/PM2600		PCB assy 86227	
--------	---------------------	--	----------------	--

CNOAH	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CNOAL	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CNOBH	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CNOBL	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CNSER	346200	STIFTLEISTE 2X 7POL		connector male 14-pin
CN001	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN003	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN004	345489	MESSERLST. 6POL		connector male 6-pin
CN005	345489	MESSERLST. 6POL		connector male 6-pin
CN006	341937	MESSERLST. 4POL		connector male 4-pin
CN007	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN008	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN009	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN010	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN011	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN012	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN013	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN014	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN015	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN016	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN017	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN018	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN019	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN020	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN021	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN022	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN024	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN025	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN026	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN027	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN028	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN029	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN030	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN031	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN032	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN033	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN034	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
CN2HI	344862	MESSERLST. 8POL		connector male 8-pin
CN2LO	344862	MESSERLST. 8POL		connector male 8-pin
CN300	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN400	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN500	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN600	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN701	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN702	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN703	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN704	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin
CN8HI	348334	STIFTLEISTE 3POL	MLSS	connector male 3-pin

112755		PM 2600 230V POWER-AMP		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description	
CN8LO	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin	
C0001	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V	
C0002	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V	
C0003	340988	KO-FOL 0.470MF 63V 5%	cap mylar 470nF	
C0004	342967	KO-FOL 3.300MF 50V 10%	cap mylar 3.3uF	
C0005	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF	
C0006	351835	KO-EL 4700.000MF 100V 20%	cap electrolytic 4700uF/100	
C0007	351835	KO-EL 4700.000MF 100V 20%	cap electrolytic 4700uF/100	
C0008	351835	KO-EL 4700.000MF 100V 20%	cap electrolytic 4700uF/100	
C0009	351835	KO-EL 4700.000MF 100V 20%	cap electrolytic 4700uF/100	
C0010	351835	KO-EL 4700.000MF 100V 20%	cap electrolytic 4700uF/100	
C0011	351835	KO-EL 4700.000MF 100V 20%	cap electrolytic 4700uF/100	
C0012	351835	KO-EL 4700.000MF 100V 20%	cap electrolytic 4700uF/100	
C0013	351835	KO-EL 4700.000MF 100V 20%	cap electrolytic 4700uF/100	
C0014	327366	KO-EL 4.700MF 50V BIP	cap bip electr. 4.7uF/50V	
C0015	329201	KO-KER 0.10MF K 50V 20%	cap ceramic 100nF	
C0016	329201	KO-KER 0.10MF K 50V 20%	cap ceramic 100nF	
C0301	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V	
C0302	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0303	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0304	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0305	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0306	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0307	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0308	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V	
C0309	304349	KO-EL 2.200MF 50V BIP	cap bip electr. 2.2uF/50V	
C0310	301530	KO-KER 100.0PF 500V 10%	cap ceramic 100pF	
C0311	340988	KO-FOL 0.470MF 63V 5%	cap mylar 470nF	
C0312	340988	KO-FOL 0.470MF 63V 5%	cap mylar 470nF	
C0313	343533	KO-EL 220.000MF 25V	cap electrolytic 220uF/25V	
C0314	335787	KO-KER 15.0PF 100V 2%	cap ceramic 15pF	
C0315	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V	
C0316	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V	
C0317	327390	KO-FOL 470.000PF 100V 5%	cap mylar 470pF	
C0318	306059	KO-KER 3.9PF 500V0.25	cap ceramic 3.9pF	
C0319	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF	
C0320	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF	
C0321	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0322	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0323	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF	
C0324	335787	KO-KER 15.0PF 100V 2%	cap ceramic 15pF	
C0325	304349	KO-EL 2.200MF 50V BIP	cap bip electr. 2.2uF/50V	
C0326	304349	KO-EL 2.200MF 50V BIP	cap bip electr. 2.2uF/50V	
C0385	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V	
C0386	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V	
C0387	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF	
C0388	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF	
C0389	301474	KO-EL 22.000MF 16V BIP	cap bip electr. 22uF/16V	
C0401	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V	
C0402	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0403	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	
C0404	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	

112755		PM 2600 230V POWER-AMP			
Pos. Nr.	Best. Nr.				Description
Ref. No.	Part No.	Bezeichnung			
C0405	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0406	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0407	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0408	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0409	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0410	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF
C0411	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0412	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0413	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0414	335787	KO-KER	15.0PF	100V 2%	cap ceramic 15pF
C0415	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0416	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0417	327390	KO-FOL	470.000PF	100V 5%	cap mylar 470pF
C0418	306059	KO-KER	3.9PF	500V0.25	cap ceramic 3.9pF
C0419	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0420	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0421	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0422	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0423	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0424	335787	KO-KER	15.0PF	100V 2%	cap ceramic 15pF
C0425	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0426	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0485	341714	KO-SO	0.10MF	275V 20% K	safety cap 100nF/275V
C0486	341714	KO-SO	0.10MF	275V 20% K	safety cap 100nF/275V
C0487	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0488	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0489	301474	KO-EL	22.000MF	16V BIP	cap bip electr. 22uF/16V
C0501	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0502	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0503	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0504	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0505	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0506	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0507	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0508	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0509	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0510	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF
C0511	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0512	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0513	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0514	335787	KO-KER	15.0PF	100V 2%	cap ceramic 15pF
C0515	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0516	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0517	327390	KO-FOL	470.000PF	100V 5%	cap mylar 470pF
C0518	306059	KO-KER	3.9PF	500V0.25	cap ceramic 3.9pF
C0519	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0520	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0521	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0522	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0523	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0524	335787	KO-KER	15.0PF	100V 2%	cap ceramic 15pF
C0525	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V

112755		PM 2600 230V POWER-AMP			
Pos. Nr.	Best. Nr.				Description
Ref. No.	Part No.	Bezeichnung			
C0526	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0585	341714	KO-SO	0.10MF	275V 20% K	safety cap 100nF/275V
C0586	341714	KO-SO	0.10MF	275V 20% K	safety cap 100nF/275V
C0587	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0588	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0589	301474	KO-EL	22.000MF	16V BIP	cap bip electr. 22uF/16V
C0601	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0602	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0603	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0604	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0605	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0606	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0607	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0608	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0609	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0610	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF
C0611	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0612	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0613	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0614	335787	KO-KER	15.0PF	100V 2%	cap ceramic 15pF
C0615	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0616	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0617	327390	KO-FOL	470.000PF	100V 5%	cap mylar 470pF
C0618	306059	KO-KER	3.9PF	500V0.25	cap ceramic 3.9pF
C0619	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0620	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0621	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0622	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0623	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0624	335787	KO-KER	15.0PF	100V 2%	cap ceramic 15pF
C0625	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0626	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0685	341714	KO-SO	0.10MF	275V 20% K	safety cap 100nF/275V
C0686	341714	KO-SO	0.10MF	275V 20% K	safety cap 100nF/275V
C0687	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0688	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0689	301474	KO-EL	22.000MF	16V BIP	cap bip electr. 22uF/16V
C0700	337597	KO-EL	1000.000MF	50V	cap electrolytic 1000uF/50V
C0701	301524	KO-KER	47.0PF	500V 10%	cap ceramic 47pF
C0702	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0703	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0704	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0705	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0706	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0707	340244	KO-FOL	0.330MF	63V 5%	cap mylar 330nF
C0708	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0709	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0800	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0801	301472	KO-EL	10.000MF	63V	cap electrolytic 10uF/63V
C0802	301472	KO-EL	10.000MF	63V	cap electrolytic 10uF/63V
C0803	301524	KO-KER	47.0PF	500V 10%	cap ceramic 47pF
C0804	301524	KO-KER	47.0PF	500V 10%	cap ceramic 47pF

112755		PM 2600 230V POWER-AMP			
Pos. Nr.	Best. Nr.				Description
Ref. No.	Part No.	Bezeichnung			
C0805	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0806	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0807	337597	KO-EL	1000.000MF	50V	cap electrolytic 1000uF/50V
C0808	337597	KO-EL	1000.000MF	50V	cap electrolytic 1000uF/50V
D0001	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0002	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0003	304360	DIODE	1N 4007	GEGURTET	diode 1N 4002
D0004	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0005	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0006	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0007	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0301	309450	DIODZ	BZX 55C	15V 0.50W	diode zener 15V
D0302	309450	DIODZ	BZX 55C	15V 0.50W	diode zener 15V
D0303	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0304	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0305	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0306	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0307	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0308	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0309	329511	DIODZ	BZX 55C	2V4 0.50W	diode zener 2V4
D0385	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0401	309450	DIODZ	BZX 55C	15V 0.50W	diode zener 15V
D0402	309450	DIODZ	BZX 55C	15V 0.50W	diode zener 15V
D0403	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0404	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0405	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0406	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0407	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0408	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0409	329511	DIODZ	BZX 55C	2V4 0.50W	diode zener 2V4
D0485	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0501	309450	DIODZ	BZX 55C	15V 0.50W	diode zener 15V
D0502	309450	DIODZ	BZX 55C	15V 0.50W	diode zener 15V
D0503	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0504	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0505	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0506	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0507	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0508	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0509	329511	DIODZ	BZX 55C	2V4 0.50W	diode zener 2V4
D0585	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0601	309450	DIODZ	BZX 55C	15V 0.50W	diode zener 15V
D0602	309450	DIODZ	BZX 55C	15V 0.50W	diode zener 15V
D0603	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0604	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0605	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0606	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0607	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0608	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0609	329511	DIODZ	BZX 55C	2V4 0.50W	diode zener 2V4
D0685	301254	DIODE	1N 4148	AXIAL	diode 1N 4148
D0701	301254	DIODE	1N 4148	AXIAL	diode 1N 4148



112755		PM 2600 230V POWER-AMP		
Pos. Nr.	Best. Nr.			Description
Ref. No.	Part No.	Bezeichnung		
D0702	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0703	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0704	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0705	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0706	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0707	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0708	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0709	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0800	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0801	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0802	304992	DIODZ BZX 55C 6V8 0.50W		diode zener 6V8
D0803	304992	DIODZ BZX 55C 6V8 0.50W		diode zener 6V8
D0804	304360	DIODE 1N 4007 GEGURTET		diode 1N 4002
E0001	354859	RELAIS 793-P-1C-S-24V DC		relay 24V
E0002	356594	RELAIS 793-P-1A-S-TV10		relay 24V / spst
E0003	354859	RELAIS 793-P-1C-S-24V DC		relay 24V
E0385	354859	RELAIS 793-P-1C-S-24V DC		relay 24V
E0485	354859	RELAIS 793-P-1C-S-24V DC		relay 24V
E0585	354859	RELAIS 793-P-1C-S-24V DC		relay 24V
E0685	354859	RELAIS 793-P-1C-S-24V DC		relay 24V
F0001	328891	SICHER T 12.5 A 250V		fuse 12.5A slow blow
F0002	328891	SICHER T 12.5 A 250V		fuse 12.5A slow blow
F0700	302583	SICHER T 1.6 A 250V		fuse 1.6A slow blow
F0800	302583	SICHER T 1.6 A 250V		fuse 1.6A slow blow
F0801	302583	SICHER T 1.6 A 250V		fuse 1.6A slow blow
GNDALH	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
GNDAL	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
GNDLH	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
GNDL	330269	FL.STECKER 6.3/0.8		connector 6.3mm faston
G0700	331965	GLRI B 80 C1500 G		rectifier B80 C1500
G0800	331965	GLRI B 80 C1500 G		rectifier B80 C1500
H0300	343457	DICKS-NETZW. 8PIN 2%		res.network 8x10k Ohm
H0301	343457	DICKS-NETZW. 8PIN 2%		res.network 8x10k Ohm
H0400	343457	DICKS-NETZW. 8PIN 2%		res.network 8x10k Ohm
H0401	343457	DICKS-NETZW. 8PIN 2%		res.network 8x10k Ohm
H0500	343457	DICKS-NETZW. 8PIN 2%		res.network 8x10k Ohm
H0501	343457	DICKS-NETZW. 8PIN 2%		res.network 8x10k Ohm
H0600	343457	DICKS-NETZW. 8PIN 2%		res.network 8x10k Ohm
H0601	343457	DICKS-NETZW. 8PIN 2%		res.network 8x10k Ohm
I0301	338359	IC LM 308 AN		IC LM 308 A
I0302	327197	IC NE 5532 P 2FACH OP		IC NE 5532 N
I0303	307421	IC CA 3080 E OTA		IC CA 3080 E
I0304	331340	IC TL 072 CP 2FACH OP		IC TL 072 CP
I0305	327197	IC NE 5532 P 2FACH OP		IC NE 5532 N
I0401	338359	IC LM 308 AN		IC LM 308 A
I0402	327197	IC NE 5532 P 2FACH OP		IC NE 5532 N
I0403	307421	IC CA 3080 E OTA		IC CA 3080 E
I0404	331340	IC TL 072 CP 2FACH OP		IC TL 072 CP
I0405	327197	IC NE 5532 P 2FACH OP		IC NE 5532 N
I0501	338359	IC LM 308 AN		IC LM 308 A
I0502	327197	IC NE 5532 P 2FACH OP		IC NE 5532 N
I0503	307421	IC CA 3080 E OTA		IC CA 3080 E

112755		PM 2600 230V POWER-AMP		
Pos. Nr.	Best. Nr.			
Ref. No.	Part No.	Bezeichnung	Description	
I0504	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP	
I0505	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N	
I0601	338359	IC LM 308 AN	IC LM 308 A	
I0602	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N	
I0603	307421	IC CA 3080 E OTA	IC CA 3080 E	
I0604	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP	
I0605	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N	
I0700	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP	
I0701	332985	IC TL 074 CN	IC TL 074 CN	
L0385	348592	FILTERSP. 2.50UH/0.004OHM	coil 2.5uH	
L0485	348592	FILTERSP. 2.50UH/0.004OHM	coil 2.5uH	
L0585	348592	FILTERSP. 2.50UH/0.004OHM	coil 2.5uH	
L0685	348592	FILTERSP. 2.50UH/0.004OHM	coil 2.5uH	
OUTAH	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston	
OUTAL	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston	
OUTBH	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston	
OUTBL	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston	
00010	301257	TRANS BD 135-10 SOT-32	transistor BD 135-10	
Q0002	306928	TRANS BC 560 C	transistor BC 560 C	
Q0003	306928	TRANS BC 560 C	transistor BC 560 C	
Q0004	307150	TRANS BC 337-25 TO 92	transistor BC 337-25	
Q0005	306928	TRANS BC 560 C	transistor BC 560 C	
Q0006	306928	TRANS BC 560 C	transistor BC 560 C	
Q0007	301184	TRANS BC 550 C	transistor BC 550 B	
Q0008	306928	TRANS BC 560 C	transistor BC 560 C	
Q0009	306928	TRANS BC 560 C	transistor BC 560 C	
Q0010	306928	TRANS BC 560 C	transistor BC 560 C	
Q0011	306928	TRANS BC 560 C	transistor BC 560 C	
00010	348410	TRANS 2SB 1110 C	transistor 2SB 1110	
Q0301	335763	TRANS 2N 3904	transistor 2N 3904	
Q0302	348422	TRANS MPSA 42	transistor MPSA 42	
Q0303	348422	TRANS MPSA 42	transistor MPSA 42	
Q0304	335763	TRANS 2N 3904	transistor 2N 3904	
Q0305	335763	TRANS 2N 3904	transistor 2N 3904	
Q0306	335763	TRANS 2N 3904	transistor 2N 3904	
Q0307	348421	TRANS 2N 3906	transistor 2N 3906	
Q0308	348421	TRANS 2N 3906	transistor 2N 3906	
Q0309	348421	TRANS 2N 3906	transistor 2N 3906	
Q0310	348423	TRANS MPSA 92	transistor MPSA 92	
Q0311	348423	TRANS MPSA 92	transistor MPSA 92	
00010	348411	TRANS 2SD 1610 C	transistor 2SD 1610	
Q0313	348421	TRANS 2N 3906	transistor 2N 3906	
Q0314	335763	TRANS 2N 3904	transistor 2N 3904	
Q0315	348421	TRANS 2N 3906	transistor 2N 3906	
Q0316	330264	TRANS J 111	transistor J 111 A	
00010	338876	TRIAC MAC 223 A6	triac MAC 223 A6	
Q0386	348421	TRANS 2N 3906	transistor 2N 3906	
Q0387	335763	TRANS 2N 3904	transistor 2N 3904	
Q0388	348421	TRANS 2N 3906	transistor 2N 3906	
00010	348410	TRANS 2SB 1110 C	transistor 2SB 1110	
Q0401	335763	TRANS 2N 3904	transistor 2N 3904	
Q0402	348422	TRANS MPSA 42	transistor MPSA 42	

112755		PM 2600 230V POWER-AMP	
Pos. Nr.	Best. Nr.	Bezeichnung	Description
Ref. No.	Part No.		
Q0403	348422	TRANS MPSA 42	transistor MPSA 42
Q0404	335763	TRANS 2N 3904	transistor 2N 3904
Q0405	335763	TRANS 2N 3904	transistor 2N 3904
Q0406	335763	TRANS 2N 3904	transistor 2N 3904
Q0407	348421	TRANS 2N 3906	transistor 2N 3906
Q0408	348421	TRANS 2N 3906	transistor 2N 3906
Q0409	348421	TRANS 2N 3906	transistor 2N 3906
Q0410	348423	TRANS MPSA 92	transistor MPSA 92
Q0411	348423	TRANS MPSA 92	transistor MPSA 92
00010	348411	TRANS 2SD 1610 C	transistor 2SD 1610
Q0413	348421	TRANS 2N 3906	transistor 2N 3906
Q0414	335763	TRANS 2N 3904	transistor 2N 3904
Q0415	348421	TRANS 2N 3906	transistor 2N 3906
Q0416	330264	TRANS J 111	transistor J 111 A
00010	338876	TRIAC MAC 223 A6	triac MAC 223 A6
Q0486	348421	TRANS 2N 3906	transistor 2N 3906
Q0487	335763	TRANS 2N 3904	transistor 2N 3904
Q0488	348421	TRANS 2N 3906	transistor 2N 3906
00010	348410	TRANS 2SB 1110 C	transistor 2SB 1110
Q0501	335763	TRANS 2N 3904	transistor 2N 3904
Q0502	348422	TRANS MPSA 42	transistor MPSA 42
Q0503	348422	TRANS MPSA 42	transistor MPSA 42
Q0504	335763	TRANS 2N 3904	transistor 2N 3904
Q0505	335763	TRANS 2N 3904	transistor 2N 3904
Q0506	335763	TRANS 2N 3904	transistor 2N 3904
Q0507	348421	TRANS 2N 3906	transistor 2N 3906
Q0508	348421	TRANS 2N 3906	transistor 2N 3906
Q0509	348421	TRANS 2N 3906	transistor 2N 3906
Q0510	348423	TRANS MPSA 92	transistor MPSA 92
Q0511	348423	TRANS MPSA 92	transistor MPSA 92
00010	348411	TRANS 2SD 1610 C	transistor 2SD 1610
Q0513	348421	TRANS 2N 3906	transistor 2N 3906
Q0514	335763	TRANS 2N 3904	transistor 2N 3904
Q0515	348421	TRANS 2N 3906	transistor 2N 3906
Q0516	330264	TRANS J 111	transistor J 111 A
00010	338876	TRIAC MAC 223 A6	triac MAC 223 A6
Q0586	348421	TRANS 2N 3906	transistor 2N 3906
Q0587	335763	TRANS 2N 3904	transistor 2N 3904
Q0588	348421	TRANS 2N 3906	transistor 2N 3906
00010	348410	TRANS 2SB 1110 C	transistor 2SB 1110
Q0601	335763	TRANS 2N 3904	transistor 2N 3904
Q0602	348422	TRANS MPSA 42	transistor MPSA 42
Q0603	348422	TRANS MPSA 42	transistor MPSA 42
Q0604	335763	TRANS 2N 3904	transistor 2N 3904
Q0605	335763	TRANS 2N 3904	transistor 2N 3904
Q0606	335763	TRANS 2N 3904	transistor 2N 3904
Q0607	348421	TRANS 2N 3906	transistor 2N 3906
Q0608	348421	TRANS 2N 3906	transistor 2N 3906
Q0609	348421	TRANS 2N 3906	transistor 2N 3906
Q0610	348423	TRANS MPSA 92	transistor MPSA 92
Q0611	348423	TRANS MPSA 92	transistor MPSA 92
00010	348411	TRANS 2SD 1610 C	transistor 2SD 1610

112755		PM 2600 230V POWER-AMP		
Pos. Nr.	Best. Nr.			Description
Ref. No.	Part No.	Bezeichnung		
Q0613	348421	TRANS 2N 3906		transistor 2N 3906
Q0614	335763	TRANS 2N 3904		transistor 2N 3904
Q0615	348421	TRANS 2N 3906		transistor 2N 3906
Q0616	330264	TRANS J 111		transistor J 111 A
00010	338876	TRIAC MAC 223 A6		triac MAC 223 A6
Q0686	348421	TRANS 2N 3906		transistor 2N 3906
Q0687	335763	TRANS 2N 3904		transistor 2N 3904
Q0688	348421	TRANS 2N 3906		transistor 2N 3906
Q0700	304591	TRANS BD 245 C		transistor BD 245 C
Q0701	307150	TRANS BC 337-25	TO 92	transistor BC 337-25
Q0702	307150	TRANS BC 337-25	TO 92	transistor BC 337-25
Q0703	301184	TRANS BC 550 C		transistor BC 550 B
Q0704	301184	TRANS BC 550 C		transistor BC 550 B
Q0705	301184	TRANS BC 550 C		transistor BC 550 B
Q0706	301184	TRANS BC 550 C		transistor BC 550 B
Q0707	301184	TRANS BC 550 C		transistor BC 550 B
Q0800	304591	TRANS BD 245 C		transistor BD 245 C
Q0801	307150	TRANS BC 337-25	TO 92	transistor BC 337-25
Q0802	307150	TRANS BC 337-25	TO 92	transistor BC 337-25
Q0803	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
Q0804	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
R0001	348550	WI-SO NTC 10 OHM	K	safety resistor 10 Ohm
R0002	348550	WI-SO NTC 10 OHM	K	safety resistor 10 Ohm
R0302	334910	WI-SCH 6.20 KOHM	2.00W 5%	resistor 6.2 kOhm 2watt
R0305	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0325	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0330	334910	WI-SCH 6.20 KOHM	2.00W 5%	resistor 6.2 kOhm 2watt
R0385	341713	WI-DR 4.70 OHM	4.00W 5%	resistor 4.70 Ohm 4watt
R0386	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0387	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0388	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0389	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0391	302032	WI-SCH 470.00 OHM	2.00W 5%	resistor 470 Ohm 2watt
R0402	334910	WI-SCH 6.20 KOHM	2.00W 5%	resistor 6.2 kOhm 2watt
R0405	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0425	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0430	334910	WI-SCH 6.20 KOHM	2.00W 5%	resistor 6.2 kOhm 2watt
R0485	341713	WI-DR 4.70 OHM	4.00W 5%	resistor 4.70 Ohm 4watt
R0486	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0487	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0488	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0489	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0491	302032	WI-SCH 470.00 OHM	2.00W 5%	resistor 470 Ohm 2watt
R0502	334910	WI-SCH 6.20 KOHM	2.00W 5%	resistor 6.2 kOhm 2watt
R0505	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0525	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0530	334910	WI-SCH 6.20 KOHM	2.00W 5%	resistor 6.2 kOhm 2watt
R0585	341713	WI-DR 4.70 OHM	4.00W 5%	resistor 4.70 Ohm 4watt
R0586	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0587	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0588	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt
R0589	348590	WI-DR 8.20 OHM	4.00W 5%	resistor 8.20 Ohm 4watt

112755		PM 2600 230V POWER-AMP		
Pos. Nr.	Best. Nr.			
Ref. No.	Part No.	Bezeichnung	Description	
R0591	302032	WI-SCH 470.00 OHM 2.00W 5%	resistor 470 Ohm 2watt	
R0602	334910	WI-SCH 6.20 KOHM 2.00W 5%	resistor 6.2 kOhm 2watt	
R0605	329215	WI-SI 10.00 OHM 0.30W 5%	safety resistor 10.0 Ohm	
R0625	329215	WI-SI 10.00 OHM 0.30W 5%	safety resistor 10.0 Ohm	
R0630	334910	WI-SCH 6.20 KOHM 2.00W 5%	resistor 6.2 kOhm 2watt	
R0685	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt	
R0686	348590	WI-DR 8.20 OHM 4.00W 5%	resistor 8.20 Ohm 4watt	
R0687	348590	WI-DR 8.20 OHM 4.00W 5%	resistor 8.20 Ohm 4watt	
R0688	348590	WI-DR 8.20 OHM 4.00W 5%	resistor 8.20 Ohm 4watt	
R0689	348590	WI-DR 8.20 OHM 4.00W 5%	resistor 8.20 Ohm 4watt	
R0691	302032	WI-SCH 470.00 OHM 2.00W 5%	resistor 470 Ohm 2watt	
R0806	301676	WI-DR 10.00 OHM 5.00W 5%	resistor 10.0 Ohm 5watt	
R0809	301676	WI-DR 10.00 OHM 5.00W 5%	resistor 10.0 Ohm 5watt	
S0001	327947	SCHALTELEMENT C42315-A1347-	switch element on/off	
S0003	338886	SCHALTER-SCHIEBE L202-02-1-	switch slide	
S0300	327947	SCHALTELEMENT C42315-A1347-	switch element on/off	
S0400	327947	SCHALTELEMENT C42315-A1347-	switch element on/off	
S0500	327947	SCHALTELEMENT C42315-A1347-	switch element on/off	
S0600	327947	SCHALTELEMENT C42315-A1347-	switch element on/off	
S0700	327947	SCHALTELEMENT C42315-A1347-	switch element on/off	
VR300	348486	WI-TRI 47.00 KOHM LIN	pot trim 47k Ohm lin	
VR400	348486	WI-TRI 47.00 KOHM LIN	pot trim 47k Ohm lin	
VR500	348486	WI-TRI 47.00 KOHM LIN	pot trim 47k Ohm lin	
VR600	348486	WI-TRI 47.00 KOHM LIN	pot trim 47k Ohm lin	
VR700	348675	WI-TRI 2.50 KOHM LIN	pot trim 2.5k Ohm lin	
00015	306838	SICHER-HALTER FAP	fuse holder	
00016	306838	SICHER-HALTER FAP	fuse holder	
00017	306838	SICHER-HALTER FAP	fuse holder	
00020	328390	SICHER-HALTER FAU	fuse holder	
00025	328391	SICHER-HALTER-KAPPE FEK	fuse holder carrier	

822298		PCBAR#PM2600		pcb assy 82229
B0001	351815	BUCHSE-FL. XLR 3POL SW	xlr connector female 3-pole	
B0002	351816	STECKER-FL. XLR 3POL PRINTB	xlr connector male 3-pin	
B0003	351815	BUCHSE-FL. XLR 3POL SW	xlr connector female 3-pole	
B0004	351816	STECKER-FL. XLR 3POL PRINTB	xlr connector male 3-pin	
CN001	344862	MESSERLST. 8POL	connector male 8-pin	
CN008	349105	MESSERLST. 20POL	connector male 20-pin	
CN01X	344862	MESSERLST. 8POL	connector male 8-pin	
CN03X	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin	
CN04X	345489	MESSERLST. 6POL	connector male 6-pin	
CN05X	345489	MESSERLST. 6POL	connector male 6-pin	
CN06X	341937	MESSERLST. 4POL	connector male 4-pin	
CN08X	349105	MESSERLST. 20POL	connector male 20-pin	
CN300	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin	
CN400	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin	
CN500	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin	
CN600	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin	
C0001	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V	
C0002	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V	
C0003	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF	

112755		PM 2600 230V POWER-AMP			
Pos. Nr.	Best. Nr.				Description
Ref. No.	Part No.	Bezeichnung			
C0004	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0005	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0006	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0007	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0008	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0009	301472	KO-EL	10.000MF	63V	cap electrolytic 10uF/63V
C0010	301472	KO-EL	10.000MF	63V	cap electrolytic 10uF/63V
C0011	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0012	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0013	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0014	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0015	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0016	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0017	340524	KO-EL	100.000MF	16V	cap electrolytic 100uF/16V
C0018	340524	KO-EL	100.000MF	16V	cap electrolytic 100uF/16V
C0019	340524	KO-EL	100.000MF	16V	cap electrolytic 100uF/16V
C0020	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0021	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0022	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0023	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0024	301472	KO-EL	10.000MF	63V	cap electrolytic 10uF/63V
C0025	301472	KO-EL	10.000MF	63V	cap electrolytic 10uF/63V
C0026	340524	KO-EL	100.000MF	16V	cap electrolytic 100uF/16V
C0027	340524	KO-EL	100.000MF	16V	cap electrolytic 100uF/16V
C0028	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0029	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0030	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0031	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0032	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0033	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0034	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0035	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0036	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0037	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0038	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0039	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0040	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0041	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0042	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0043	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0044	340522	KO-EL	10.000MF	35V	cap electrolytic 10uF/35
C0045	340522	KO-EL	10.000MF	35V	cap electrolytic 10uF/35
C0046	345461	KO-KER	680.0PF	100V 10%	cap ceramic 680pF
C0047	345461	KO-KER	680.0PF	100V 10%	cap ceramic 680pF
C0048	340523	KO-EL	22.000MF	16V	cap electrolytic 22uF/16V
C0049	340523	KO-EL	22.000MF	16V	cap electrolytic 22uF/16V
C0050	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0051	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0052	345461	KO-KER	680.0PF	100V 10%	cap ceramic 680pF
C0053	345461	KO-KER	680.0PF	100V 10%	cap ceramic 680pF
C0054	340523	KO-EL	22.000MF	16V	cap electrolytic 22uF/16V
C0055	340523	KO-EL	22.000MF	16V	cap electrolytic 22uF/16V

112755		PM 2600 230V POWER-AMP			
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung			Description
C0056	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0060	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0061	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0062	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0063	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0070	304349	KO-EL	2.200MF	50V BIP	cap bip electr. 2.2uF/50V
C0071	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0100	340244	KO-FOL	0.330MF	63V 5%	cap mylar 330nF
C0101	340244	KO-FOL	0.330MF	63V 5%	cap mylar 330nF
C0102	344109	KO-FOL	0.056MF	63V 5%	cap mylar 56nF
C0103	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0104	327389	KO-FOL	220.000PF	100V 5%	cap mylar 220pF
C0200	340244	KO-FOL	0.330MF	63V 5%	cap mylar 330nF
C0201	340244	KO-FOL	0.330MF	63V 5%	cap mylar 330nF
C0202	344109	KO-FOL	0.056MF	63V 5%	cap mylar 56nF
C0203	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0204	327389	KO-FOL	220.000PF	100V 5%	cap mylar 220pF
C0301	332962	KO-EL	470.000MF	25V	cap electrolytic 470uF/25V
C0303	332962	KO-EL	470.000MF	25V	cap electrolytic 470uF/25V
C0331	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0332	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0333	300302	KO-FOL	1200.000PF	100V 5%	cap mylar 1200pF
C0334	342933	KO-FOL	0.022MF	100V 5%	cap mylar 22nF
C0401	332962	KO-EL	470.000MF	25V	cap electrolytic 470uF/25V
C0403	332962	KO-EL	470.000MF	25V	cap electrolytic 470uF/25V
C0431	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0432	344109	KO-FOL	0.056MF	63V 5%	cap mylar 56nF
C0501	332962	KO-EL	470.000MF	25V	cap electrolytic 470uF/25V
C0503	332962	KO-EL	470.000MF	25V	cap electrolytic 470uF/25V
C0531	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0532	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0533	300302	KO-FOL	1200.000PF	100V 5%	cap mylar 1200pF
C0534	342933	KO-FOL	0.022MF	100V 5%	cap mylar 22nF
C0601	332962	KO-EL	470.000MF	25V	cap electrolytic 470uF/25V
C0603	332962	KO-EL	470.000MF	25V	cap electrolytic 470uF/25V
C0631	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0632	344109	KO-FOL	0.056MF	63V 5%	cap mylar 56nF
C0635	340524	KO-EL	100.000MF	16V	cap electrolytic 100uF/16V
D0020	304992	DIODZ BZX 55C	6V8	0.50W	diode zener 6V8
D0021	304992	DIODZ BZX 55C	6V8	0.50W	diode zener 6V8
D0022	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0023	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0024	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0025	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0026	336398	LED GN 3MM TLHG	4400/01		LED green 3mm
D0027	336398	LED GN 3MM TLHG	4400/01		LED green 3mm
D0030	304992	DIODZ BZX 55C	6V8	0.50W	diode zener 6V8
D0031	304992	DIODZ BZX 55C	6V8	0.50W	diode zener 6V8
D0032	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0033	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0034	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0035	301254	DIODE 1N 4148	AXIAL		diode 1N 4148

112755		PM 2600 230V POWER-AMP		
Pos. Nr.	Best. Nr.			
Ref. No.	Part No.	Bezeichnung	Description	
D0036	336398	LED GN 3MM TLHG 4400/01	LED green 3mm	
D0037	336398	LED GN 3MM TLHG 4400/01	LED green 3mm	
D0040	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8	
D0041	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8	
D0042	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0043	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0044	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0045	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0046	336398	LED GN 3MM TLHG 4400/01	LED green 3mm	
D0050	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8	
D0051	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8	
D0052	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0053	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0054	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0055	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0056	336398	LED GN 3MM TLHG 4400/01	LED green 3mm	
D0060	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8	
D0061	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8	
D0062	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0063	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0064	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0065	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0066	336398	LED GN 3MM TLHG 4400/01	LED green 3mm	
D0070	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8	
D0071	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8	
D0072	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0073	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0074	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0075	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0076	336398	LED GN 3MM TLHG 4400/01	LED green 3mm	
D0080	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0081	336399	LED RT 3MM TLUR 4401	LED red 3mm	
D0082	336397	LED GE 3MM TLHY 4400/01	LED yellow 3mm	
D0083	336397	LED GE 3MM TLHY 4400/01	LED yellow 3mm	
D0084	336397	LED GE 3MM TLHY 4400/01	LED yellow 3mm	
D0085	336398	LED GN 3MM TLHG 4400/01	LED green 3mm	
D0086	336397	LED GE 3MM TLHY 4400/01	LED yellow 3mm	
D0087	336397	LED GE 3MM TLHY 4400/01	LED yellow 3mm	
D0300	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002	
D0301	341613	DIODZ BZX 55C 51V 0.50W	diode zener 51V 0,5watt	
D0302	301310	DIODZ BZX 55C 20V 0.50W	diode zener 20V 0,5watt	
D0303	301297	DIODE BAT 85 SCHOTTKY	diode BAT 85	
D0305	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0400	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002	
D0401	341613	DIODZ BZX 55C 51V 0.50W	diode zener 51V 0,5watt	
D0402	301310	DIODZ BZX 55C 20V 0.50W	diode zener 20V 0,5watt	
D0403	301297	DIODE BAT 85 SCHOTTKY	diode BAT 85	
D0405	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0500	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002	
D0501	341613	DIODZ BZX 55C 51V 0.50W	diode zener 51V 0,5watt	
D0502	301310	DIODZ BZX 55C 20V 0.50W	diode zener 20V 0,5watt	
D0503	301297	DIODE BAT 85 SCHOTTKY	diode BAT 85	



112755		PM 2600 230V POWER-AMP		
Pos. Nr.	Best. Nr.			
Ref. No.	Part No.	Bezeichnung	Description	
D0505	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
D0600	304360	DIODE 1N 4007	GEGURTET	diode 1N 4002
D0601	341613	DIODZ BZX 55C	51V 0.50W	diode zener 51V 0,5watt
D0602	301310	DIODZ BZX 55C	20V 0.50W	diode zener 20V 0,5watt
D0603	301297	DIODE BAT 85	SCHOTTKY	diode BAT 85
D0605	301254	DIODE 1N 4148	AXIAL	diode 1N 4148
H0001	343456	DICKS-NETZW.	8PIN 2%	res.network 8x4k7 Ohm
H0002	343456	DICKS-NETZW.	8PIN 2%	res.network 8x4k7 Ohm
H0003	343457	DICKS-NETZW.	8PIN 2%	res.network 8x10k Ohm
H0004	343457	DICKS-NETZW.	8PIN 2%	res.network 8x10k Ohm
I0001	354934	IC NJM 2068 L	SINGLE IN	IC NJM 2068 L
I0002	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0020	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0030	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0040	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0050	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0060	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0070	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0100	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0101	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0200	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0201	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0300	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0301	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0400	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0401	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0500	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0501	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0600	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0601	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
J003X	327779	STIFTELEISTE	3POL STL 11 S	connector male 3-pin
J004X	327779	STIFTELEISTE	3POL STL 11 S	connector male 3-pin
J005P	327779	STIFTELEISTE	3POL STL 11 S	connector male 3-pin
J006X	327779	STIFTELEISTE	3POL STL 11 S	connector male 3-pin
Q0080	307150	TRANS BC 337-25	TO 92	transistor BC 337-25
Q0081	307150	TRANS BC 337-25	TO 92	transistor BC 337-25
Q0300	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
Q0301	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
Q0400	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
Q0401	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
Q0500	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
Q0501	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
Q0600	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
Q0601	307430	TRANS BC 327-25	TO 92	transistor BC 327-25
R0001	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0002	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0003	340299	WI-SI 2.20 OHM	0.30W 5%	safety resistor 2.20 Ohm
R0004	340299	WI-SI 2.20 OHM	0.30W 5%	safety resistor 2.20 Ohm
R0005	340299	WI-SI 2.20 OHM	0.30W 5%	safety resistor 2.20 Ohm
R0006	340299	WI-SI 2.20 OHM	0.30W 5%	safety resistor 2.20 Ohm
R0008	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm
R0009	329215	WI-SI 10.00 OHM	0.30W 5%	safety resistor 10.0 Ohm

112755		PM 2600 230V POWER-AMP	
Pos. Nr.	Best. Nr.	Bezeichnung	Description
Ref. No.	Part No.		
S00HI	351937	SCHALTER-DREH 3X4 EB.PRINT	switch 3x4
S0300	327947	SCHALTELEMENT C42315-A1347-	switch element on/off
S0400	327947	SCHALTELEMENT C42315-A1347-	switch element on/off
S0500	327947	SCHALTELEMENT C42315-A1347-	switch element on/off
S0600	327947	SCHALTELEMENT C42315-A1347-	switch element on/off
VRLO	351946	P-DREH 2X 10KOHM LIN B	potentiometer 2x 10k Ohm B
VR100	348430	P-DREH 10KOHM LIN B	potentiometer 10k Ohm lin
VR200	348430	P-DREH 10KOHM LIN B	potentiometer 10k Ohm lin
00010	332452	KODIERBRÜCKE 330.0101 SW	shorting plug