

## Ersatzteilliste - Bill of Materials

112740 POWERMAX 230 EUROPA			
Pos. Nr.	Best. Nr.		
Ref. No.	Part No.	Bezeichnung	Description

Zubehör	Accessories & packing material
---------	--------------------------------

345095	FUSS-GUMMI	12.7X 3.5	rubber foot
356332	BEDIENUNGSANL.	POWERMAX230	owner's manual
300425	KABEL-NETZ	2.0 M 10A	power cable Europe
335228	KRT. DRP	515X365X100	carton
335229	STYROPOR-EINLAGE	DRP	carton filler foam
333375	SCHUTZHÜLLE	500X700X0,05	poly bag

Mechanische Teile	Cabinet material
-------------------	------------------

356348	DK 11	SW/GR/SW C 6FL	knob
347430	TK 10X6	SW 2,8	push button black 10x6
337059	KNOPF-TASTE	12X7 SW 3.3	push button black 12x7
356205	FB.POWERMAX	BED	front panel
358053	DEC.POWERMAX 230	BED	top cover

822278 PCBAR#PX 230	main pcb assy 82227
---------------------	---------------------

C0001	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0002	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0003	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0004	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0005	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0006	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0007	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0008	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0009	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0010	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0013	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0014	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0015	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0016	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0017	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0018	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0019	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF
C0020	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF
C0021	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0022	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0023	344109	KO-FOL	0.056MF	63V 5%	cap mylar 56nF
C0024	344109	KO-FOL	0.056MF	63V 5%	cap mylar 56nF
C0025	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0026	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF
C0027	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0028	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V
C0029	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0030	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0031	344105	KO-FOL	0.027MF	100V 5%	cap mylar 27nF
C0032	344105	KO-FOL	0.027MF	100V 5%	cap mylar 27nF

112740 POWERMAX 230 EUROPA						
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung			Description	
C0033	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF	
C0034	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF	
C0035	344105	KO-FOL	0.027MF	100V 5%	cap mylar 27nF	
C0036	344105	KO-FOL	0.027MF	100V 5%	cap mylar 27nF	
C0037	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF	
C0038	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF	
C0039	337238	KO-FOL	0.680MF	63V 5%	cap mylar 680nF	
C0040	337238	KO-FOL	0.680MF	63V 5%	cap mylar 680nF	
C0041	337238	KO-FOL	0.680MF	63V 5%	cap mylar 680nF	
C0042	337238	KO-FOL	0.680MF	63V 5%	cap mylar 680nF	
C0043	344109	KO-FOL	0.056MF	63V 5%	cap mylar 56nF	
C0044	344109	KO-FOL	0.056MF	63V 5%	cap mylar 56nF	
C0045	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF	
C0046	340988	KO-FOL	0.470MF	63V 5%	cap mylar 470nF	
C0047	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0048	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0053	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0054	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0055	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0056	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF	
C0057	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF	
C0058	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF	
C0059	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0060	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0061	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0062	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF	
C0063	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0064	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0065	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0066	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0067	327394	KO-FOL	5600.000PF	63V 5%	cap mylar 5600pF	
C0068	327394	KO-FOL	5600.000PF	63V 5%	cap mylar 5600pF	
C0069	300050	KO-FOL	330.000PF	100V 5%	cap mylar 330pF	
C0070	300050	KO-FOL	330.000PF	100V 5%	cap mylar 330pF	
C0071	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF	
C0072	301530	KO-KER	100.0PF	500V 10%	cap ceramic 100pF	
C0075	326924	KO-FOL	2200.000PF	100V 5%	cap mylar 2200pF	
C0076	326924	KO-FOL	2200.000PF	100V 5%	cap mylar 2200pF	
C0077	342934	KO-FOL	0.033MF	100V 5%	cap mylar 33nF	
C0078	342934	KO-FOL	0.033MF	100V 5%	cap mylar 33nF	
C0079	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0080	343532	KO-EL	100.000MF	25V	cap electrolytic 100uF/25V	
C0081	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF	
C0082	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF	
C0083	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V	
C0084	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V	
C0085	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF	
C0086	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF	
C0087	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF	
C0088	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF	
C0089	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF	
C0090	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF	

112740 POWERMAX 230 EUROPA					
Pos. Nr.	Best. Nr.	Bezeichnung			Description
Ref. No.	Part No.				
C0091	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0092	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0093	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0094	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0095	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0096	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0097	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0098	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0099	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0100	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0101	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0102	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0103	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0104	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0105	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0106	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0107	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0108	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0109	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0110	301558	KO-KER	33.0PF	100V 2%	cap ceramic 33pF
C0111	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0112	343533	KO-EL	220.000MF	25V	cap electrolytic 220uF/25V
C0113	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0114	301543	KO-KER	330.0PF	500V 10%	cap ceramic 330pF
C0115	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0116	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0117	341714	KO-SO	0.10MF 275V	20% K	safety cap 100nF/275V
C0118	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0119	356661	KO-EL	2200.000MF	35V	cap electrolytic 2200uF/35V
C0120	356661	KO-EL	2200.000MF	35V	cap electrolytic 2200uF/35V
C0121	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0122	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0123	301478	KO-EL	22.000MF	63V	cap electrolytic 22uF/63V
C0124	301478	KO-EL	22.000MF	63V	cap electrolytic 22uF/63V
C0125	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0126	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0127	343534	KO-EL	1000.000MF	16V	cap electrolytic 1000uF/16V
C0128	343534	KO-EL	1000.000MF	16V	cap electrolytic 1000uF/16V
C0129	342923	KO-FOL	0.220MF	63V 5%	cap mylar 220nF
C0130	307445	KO-EL	10.000MF	35V	cap electrolytic 10uF/35V
C0131	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0132	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0133	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0134	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0135	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0136	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0137	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0138	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0139	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0140	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0141	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0142	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF

112740 POWERMAX 230 EUROPA					
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung			Description
C0143	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0144	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0145	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0146	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0147	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0148	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0149	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0150	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0151	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0152	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0153	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0154	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0155	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0156	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0157	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0158	343530	KO-EL	47.000MF	50V	cap electrolytic 47uF/50V
C0159	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0160	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0161	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0162	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0163	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0164	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0165	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0166	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0167	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0168	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0169	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0170	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0171	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0172	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0173	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0174	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0175	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0176	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0177	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0178	301453	KO-EL	1.000MF	50V	cap electrolytic 1uF/50V
C0179	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0180	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0181	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
C0182	329021	KO-KER	0.10MF	100V 20%	cap ceramic 100nF
D0001	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0002	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0003	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0004	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0005	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0006	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0007	304360	DIODE 1N 4007	GEGURTET		diode 1N 4002
D0008	304360	DIODE 1N 4007	GEGURTET		diode 1N 4002
D0014	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0015	301254	DIODE 1N 4148	AXIAL		diode 1N 4148
D0016	304360	DIODE 1N 4007	GEGURTET		diode 1N 4002
D0017	304360	DIODE 1N 4007	GEGURTET		diode 1N 4002

112740 POWERMAX 230 EUROPA				
Pos. Nr.	Best. Nr.			
Ref. No.	Part No.	Bezeichnung	Description	
D0018	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002	
D0019	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002	
D0030	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0031	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0032	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0033	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0034	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0035	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0036	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0037	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0038	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0039	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0040	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0041	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0042	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0043	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0044	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0045	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0046	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0047	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0048	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0049	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0050	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0051	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0052	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0053	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0054	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0055	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0056	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0057	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0058	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0059	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0060	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0061	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
D0062	301254	DIODE 1N 4148 AXIAL	diode 1N 4148	
E0001	356745	RELAIS M4-24H	relay 24V	
E0002	356745	RELAIS M4-24H	relay 24V	
E0003	356745	RELAIS M4-24H	relay 24V	
E0004	356745	RELAIS M4-24H	relay 24V	
E0005	356745	RELAIS M4-24H	relay 24V	
F0001	356996	SICHER T 80 MA 250V	fuse 80mA slow blow	
F0002	302579	SICHER T 500 MA 250V	fuse 500mA slow blow	
F0003	302579	SICHER T 500 MA 250V	fuse 500mA slow blow	
H0001	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k	
H0002	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k	
I0001	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP	
I0002	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N	
I0003	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N	
I0004	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N	
I0005	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP	
I0006	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP	
I0007	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP	

112740 POWERMAX 230 EUROPA				
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung		Description
I0008	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0009	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0010	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0011	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0012	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0013	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0014	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0015	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0016	331340	IC TL 072 CP	2FACH OP	IC TL 072 CP
I0018	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0019	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0020	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0021	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0022	327197	IC NE 5532 P	2FACH OP	IC NE 5532 N
I0023	354929	IC SPNG.REG. LM 337 T		IC LM 337 voltage regulator
I0024	354199	IC SPNG.REG. LM 317 T		IC LM 317 voltage regulator
I0025	343502	IC LM 2901 N		IC LM 2901
I0026	343502	IC LM 2901 N		IC LM 2901
I0027	343502	IC LM 2901 N		IC LM 2901
I0028	343502	IC LM 2901 N		IC LM 2901
JS001	351816	STECKER-FL. XLR 3POL PRINTB		xlr connector male 3-pin
JS002	351816	STECKER-FL. XLR 3POL PRINTB		xlr connector male 3-pin
JS003	351815	BUCHSE-FL. XLR 3POL SW		xlr connector female
JS004	351815	BUCHSE-FL. XLR 3POL SW		xlr connector female
JS005	351816	STECKER-FL. XLR 3POL PRINTB		xlr connector male 3-pin
JS006	351816	STECKER-FL. XLR 3POL PRINTB		xlr connector male 3-pin
JS007	351816	STECKER-FL. XLR 3POL PRINTB		xlr connector male 3-pin
JS008	351816	STECKER-FL. XLR 3POL PRINTB		xlr connector male 3-pin
JS009	351816	STECKER-FL. XLR 3POL PRINTB		xlr connector male 3-pin
JS010	338835	STECKER-KALTGERÄTE		connector male mains
LED11	356749	LED RT 3MM LOW CURRENT		led red
LED12	356749	LED RT 3MM LOW CURRENT		led red
LED13	356749	LED RT 3MM LOW CURRENT		led red
LED22	356746	LED RT/GN 3MM LOW CURRENT		led red/green
LED23	356746	LED RT/GN 3MM LOW CURRENT		led red/green
LED24	356746	LED RT/GN 3MM LOW CURRENT		led red/green
LED25	356746	LED RT/GN 3MM LOW CURRENT		led red/green
LED26	356746	LED RT/GN 3MM LOW CURRENT		led red/green
LED27	356746	LED RT/GN 3MM LOW CURRENT		led red/green
LED28	356746	LED RT/GN 3MM LOW CURRENT		led red/green
LED29	356843	LED GN 3MM LOW CURRENT		led green
Q0001	307150	TRANS BC 337-25 TO 92		transistor BC 337-25
Q0002	306928	TRANS BC 560 C		transistor BC 560 C
Q0003	306928	TRANS BC 560 C		transistor BC 560 C
Q0004	307150	TRANS BC 337-25 TO 92		transistor BC 337-25
Q0005	306928	TRANS BC 560 C		transistor BC 560 C
Q0006	306928	TRANS BC 560 C		transistor BC 560 C
Q0007	307150	TRANS BC 337-25 TO 92		transistor BC 337-25
R0242	329215	WI-SI 10.00 OHM 0.30W 5%		safety resistor 10 Ohm
R0243	329215	WI-SI 10.00 OHM 0.30W 5%		safety resistor 10 Ohm
R0244	329215	WI-SI 10.00 OHM 0.30W 5%		safety resistor 10 Ohm
R0245	329215	WI-SI 10.00 OHM 0.30W 5%		safety resistor 10 Ohm

112740 POWERMAX 230 EUROPA						
Pos. Nr.	Best. Nr.	Bezeichnung			Description	
Ref. No.	Part No.					
R0246	329215	WI-SI	10.00	OHM 0.30W 5%	safety resistor 10 Ohm	
R0247	329215	WI-SI	10.00	OHM 0.30W 5%	safety resistor 10 Ohm	
R0248	329215	WI-SI	10.00	OHM 0.30W 5%	safety resistor 10 Ohm	
R0249	329215	WI-SI	10.00	OHM 0.30W 5%	safety resistor 10 Ohm	
S0001	349114	SCHALTER-NETZ			mains switch	
S0002	340434	SCHALTER-SCHIEBE 2XUM			switch slide	
S0004	344038	SCHALTER-RAST 4XUM			switch 4pdt latching	
S0005	344038	SCHALTER-RAST 4XUM			switch 4pdt latching	
S0006	344037	SCHALTER-RAST 2XUM			switch dpdt latching	
T0001	356744	NETZTRAFO-RINGKERN	10 VA		mains transformer 230V	
VR001	356751	P-DREH	10KOHM LIN	B	potentiometer 10k lin	
VR002	356751	P-DREH	10KOHM LIN	B	potentiometer 10k lin	
VR003	356750	P-DREH 2X	10KOHM LIN	B	potentiometer 2x10k lin	
VR004	356752	P-DREH 4X	10KOHM LOG	NEG E	potentiometer 4x10k -log	
VR005	356752	P-DREH 4X	10KOHM LOG	NEG E	potentiometer 4x10k -log	
VR006	356750	P-DREH 2X	10KOHM LIN	B	potentiometer 2x10k lin	
VR007	356751	P-DREH	10KOHM LIN	B	potentiometer 10k lin	
VR008	356750	P-DREH 2X	10KOHM LIN	B	potentiometer 2x10k lin	
VR009	356750	P-DREH 2X	10KOHM LIN	B	potentiometer 2x10k lin	
VR010	356750	P-DREH 2X	10KOHM LIN	B	potentiometer 2x10k lin	
VR011	356753	WI-TRI	5.00 KOHM	LIN	trim pot 5k lin	
VR012	356753	WI-TRI	5.00 KOHM	LIN	trim pot 5k lin	
VR013	356753	WI-TRI	5.00 KOHM	LIN	trim pot 5k lin	
VR014	356753	WI-TRI	5.00 KOHM	LIN	trim pot 5k lin	
VR015	356753	WI-TRI	5.00 KOHM	LIN	trim pot 5k lin	
00005	328390	SICHER-HALTER	FAU		fuse holder	
00010	328391	SICHER-HALTER-KAPPE	FEK		fuse holder carrier	
00015	303576	SICHER-HALTE-FEDER			fuse clip	