

Ersatzteilliste - Bill of Materials

112532 L 300 ENDST.2X150W			
Pos. Nr.	Best. Nr.		
Ref. No.	Part No.	Bezeichnung	Description

Zubehör	Accessories & packing material
---------	--------------------------------

349519	BEDIENUNGSANL. L-SERIE	owner's manual
349522	FILTER-LÜFTER L 1000	air filter
357781	SECHSKT.STIFTSCHLÜSSEL 3	hex socket wrench
353105	KRT. 2 HE "DY." 556X507X178	carton
349568	STYROPOR-EINLAGE 2 HE 86MM	carton filler foam
342799	STYROPOR-PL. 500X380X50	styrofoam
337053	SCHUTZHÜLLE 650X800X0,08	poly bag

Mechanische Teile	Cabinet material
-------------------	------------------

B0010	341343	BUCHSE-SPEAKON-VIERECK 4POL	speaker socket 4-pole
S0010	346720	SCHALTER-NETZ ESB-99888V	power switch
	347348	DK 22 SW/GA C 6FL	rotary knob black
	341382	KNOPF-TASTE 20X8 SW 3.3	push button black
	349528	HUTSTOPFEN H7 18,5MM	plug, hole
	335589	FUSS-GUMMI SJ 5009 SW	rubber foot
	349635	KABEL-NETZ BEARB.AUS 349508	mains cord
	349610	KABEL-KONFEKT 10POL 0.520M	ribbon cable assy 10-way
	349611	KABEL-KONFEKT 8POL 0.510M	ribbon cable assy 8-way
	349612	KABEL-KONFEKT 8POL 0.400M	ribbon cable assy 8-way
	349626	KABEL-KONFEKT 10POL 0.560M	ribbon cable assy 10-way
	349627	KABEL-KONFEKT 4POL 0.320M	ribbon cable assy 4-way
	348461	KABEL-KONFEKT 4POL 0.530M	ribbon cable assy 4-way
	349306	GRIFF 65 MM ANTHR. 2HE	handle 2HU
	348415	LÜFTER TYP FBA08A24H DC	fan dc 24V
	349564	FB.L 300 BED	front panel L300
	351357	BLAUF.L3-1000/P550+1050 LAC	front panel grille
	349618	RW.L 300 BED	rear panel L300
	351352	DEC.2HE DEM-LACK/L3-550 LAC	top cover
	348606	RKT L300 230V	mains transformer 230V
	348309	WI-SO PTC K155 100GRAD	resistor ptc
	348341	FEDERLEISTE 3POL CE100-	connector female 3-pole

813068	PCB+A:L 300	PCB assy input
---------------	--------------------	-----------------------

B0001	351815	BUCHSE-FL. XLR 3POL PRINTB	xlr connector female 3-pole
B0002	351816	STECKER-FL. XLR 3POL PRINTB	xlr connector male 3-pin
B0003	351815	BUCHSE-FL. XLR 3POL PRINTB	xlr connector female 3-pole
B0004	351816	STECKER-FL. XLR 3POL PRINTB	xlr connector male 3-pin
CN001	344975	MESSERLST. 10POL	connector male 10-pin
CN002	306395	FEDERLEISTE 2,5MM O 7POL	connector female 7-pole
CN003	348334	STIFTLAISTE 3POL MLSS	connector male 3-pin
CN004	344975	MESSERLST. 10POL	connector male 10-pin
CN005	337593	FEDERLEISTE 2,5MM O 5POL	connector female 5-pole
CN006	344975	MESSERLST. 10POL	connector male 10-pin
CN007	343516	FL.STECKER 4.8/0.5	connector 4.8mm faston
CN008	341937	MESSERLST. 4POL	connector male 4-pin
CN009	341937	MESSERLST. 4POL	connector male 4-pin

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
C0001	342937	KO-FOL 1.000MF 63V 5%	cap mylar 1uF
C0002	342937	KO-FOL 1.000MF 63V 5%	cap mylar 1uF
C0003	346976	KO-FOL 4700.000PF 100V 5%	cap mylar 4.7nF
C0004	337181	KO-FOL 0.010MF 100V 5%	cap mylar 10nF
C0005	327389	KO-FOL 220.000PF 100V 5%	cap mylar 220pF
C0006	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V
C0009	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V
C0010	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0011	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0012	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0013	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0014	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0015	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0101	342937	KO-FOL 1.000MF 63V 5%	cap mylar 1uF
C0102	342937	KO-FOL 1.000MF 63V 5%	cap mylar 1uF
C0103	346976	KO-FOL 4700.000PF 100V 5%	cap mylar 4.7nF
C0104	337181	KO-FOL 0.010MF 100V 5%	cap mylar 10nF
C0105	327389	KO-FOL 220.000PF 100V 5%	cap mylar 220pF
C0106	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V
C0109	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V
C0110	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0111	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0112	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0113	301558	KO-KER 33.0PF 100V 2%	cap ceramic 33pF
C0114	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0115	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
D0001	336398	LED GN 3MM TLHG 4400/01	LED green 3mm
D0002	336398	LED GN 3MM TLHG 4400/01	LED green 3mm
D0003	336398	LED GN 3MM TLHG 4400/01	LED green 3mm
D0004	336398	LED GN 3MM TLHG 4400/01	LED green 3mm
D0005	336399	LED RT 3MM TLUR 4401	LED red 3mm
D0006	336399	LED RT 3MM TLUR 4401	LED red 3mm
D0007	336399	LED RT 3MM TLUR 4401	LED red 3mm
D0008	336399	LED RT 3MM TLUR 4401	LED red 3mm
D0009	336398	LED GN 3MM TLHG 4400/01	LED green 3mm
D0010	336398	LED GN 3MM TLHG 4400/01	LED green 3mm
D0011	328788	DIODZ BZX 55C 5V1 0.50W	diode zener 5V1
D0012	328788	DIODZ BZX 55C 5V1 0.50W	diode zener 5V1
D0013	328788	DIODZ BZX 55C 5V1 0.50W	diode zener 5V1
D0014	328788	DIODZ BZX 55C 5V1 0.50W	diode zener 5V1
D0015	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
H0001	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k Ohm
H0002	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k Ohm
I0001	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0002	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0003	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0004	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0005	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP
J0123	340681	STIFTLEISTE 2X 3POL	connector male 2x3-pin
J0456	340681	STIFTLEISTE 2X 3POL	connector male 2x3-pin
Q0001	335763	TRANS 2N 3904	transistor 2N 3904
Q0002	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0003	307430	TRANS BC 327-25 TO 92	transistor BC 327-25

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
Q0004	348421	TRANS 2N 3906	transistor 2N 3906
Q0005	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0006	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0101	335763	TRANS 2N 3904	transistor 2N 3904
Q0102	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0103	307430	TRANS BC 327-25 TO 92	transistor BC 327-25
Q0104	348421	TRANS 2N 3906	transistor 2N 3906
S0001	348572	SCHALTER-SCHIEBE 4XUM	slide switch 4pdt
S0002	348583	SCHALTER-SCHIEBE 2XUM	slide switch dpdt
S0003	348583	SCHALTER-SCHIEBE 2XUM	slide switch dpdt
S0004	348583	SCHALTER-SCHIEBE 2XUM	slide switch dpdt
VR001	348430	P-DREH 10KOHM LIN	potentiometer 10k Ohm lin
VR002	348430	P-DREH 10KOHM LIN	potentiometer 10k Ohm lin
VR003	348487	WI-TRI 4.70 KOHM LIN	pot trim 4.7k Ohm lin
VR004	348487	WI-TRI 4.70 KOHM LIN	pot trim 4.7k Ohm lin
	332452	KODIERBRÜCKE 330.0101 SW	shorting plug
	306397	KODIERSTIFT	code plug

841528		PCBAR#L 300	PCB assy power amp
CN001	344862	MESSERLST. 8POL	connector male 8-pin
CN002	341937	MESSERLST. 4POL	connector male 4-pin
CN003	344975	MESSERLST. 10POL	connector male 10-pin
CN004	348334	STIFTELEISTE 3POL MLSS	connector male 3-pin
CN005	344862	MESSERLST. 8POL	connector male 8-pin
CN006	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN007	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN008	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN302	341937	MESSERLST. 4POL	connector male 4-pin
C0001	335787	KO-KER 15.0PF 100V 2%	cap ceramic 15pF
C0002	301530	KO-KER 100.0PF 500V 10%	cap ceramic 100pF
C0003	340988	KO-FOL 0.470MF 63V 5%	cap mylar 470nF
C0004	304349	KO-EL 2.200MF 50V BIP	cap bip electr. 2.2uF/50V
C0005	327390	KO-FOL 470.000PF 100V 5%	cap mylar 470pF
C0006	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0007	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0008	301519	KO-KER 10.0PF 500V 10%	cap ceramic 10pF
C0010	326675	KO-EL 100.000MF 10V BIP	cap bip electr. 100uF/10V
C0014	348814	KO-KER 220.0PF K 500V 2%	cap ceramic 220pF
C0015	348814	KO-KER 220.0PF K 500V 2%	cap ceramic 220pF
C0016	351452	KO-FOL 2.200MF 50V 5%	cap mylar 2.2uF
C0018	306059	KO-KER 3.9PF 500V0.25	cap ceramic 3.9pF
C0019	301474	KO-EL 22.000MF 16V BIP	cap bip electr. 22uF/16V
C0021	326675	KO-EL 100.000MF 10V BIP	cap bip electr. 100uF/10V
C0022	326675	KO-EL 100.000MF 10V BIP	cap bip electr. 100uF/10V
C0023	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF
C0024	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF
C0025	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0026	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0027	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0028	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0029	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0030	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
C0031	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
C0034	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0301	335787	KO-KER 15.0PF 100V 2%	cap ceramic 15pF
C0302	301530	KO-KER 100.0PF 500V 10%	cap ceramic 100pF
C0303	340988	KO-FOL 0.470MF 63V 5%	cap mylar 470nF
C0304	304349	KO-EL 2.200MF 50V BIP	cap bip electr. 2.2uF/50V
C0305	327390	KO-FOL 470.000PF 100V 5%	cap mylar 470pF
C0306	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0307	343532	KO-EL 100.000MF 25V	cap electrolytic 100uF/25V
C0308	301519	KO-KER 10.0PF 500V 10%	cap ceramic 10pF
C0310	326675	KO-EL 100.000MF 10V BIP	cap bip electr. 100uF/10V
C0314	348814	KO-KER 220.0PF K 500V 2%	cap ceramic 220pF
C0315	348814	KO-KER 220.0PF K 500V 2%	cap ceramic 220pF
C0316	351452	KO-FOL 2.200MF 50V 5%	cap mylar 2.2uF
C0318	306059	KO-KER 3.9PF 500V0.25	cap ceramic 3.9pF
C0319	301474	KO-EL 22.000MF 16V BIP	cap bip electr. 22uF/16V
C0321	326675	KO-EL 100.000MF 10V BIP	cap bip electr. 100uF/10V
C0322	326675	KO-EL 100.000MF 10V BIP	cap bip electr. 100uF/10V
C0323	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF
C0324	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF
C0325	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0326	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
C0330	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
C0331	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
D0002	309450	DIODZ BZX 55C 15V 0.50W	diode zener 15V
D0003	309450	DIODZ BZX 55C 15V 0.50W	diode zener 15V
D0004	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0005	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0006	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0007	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0008	307916	DIODZ BZX 55C 7V5 0.50W	diode zener 7V5
D0009	307916	DIODZ BZX 55C 7V5 0.50W	diode zener 7V5
D0010	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0011	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0012	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0014	328769	DIODE MR 752	diode MR 752
D0015	328769	DIODE MR 752	diode MR 752
D0016	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0017	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0019	329511	DIODZ BZX 55C 2V4 0.50W	diode zener 2V4
D0024	348573	DIODE BAV 20 0.40W	diode BAV 20
D0025	348573	DIODE BAV 20 0.40W	diode BAV 20
D0026	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0027	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0302	309450	DIODZ BZX 55C 15V 0.50W	diode zener 15V
D0303	309450	DIODZ BZX 55C 15V 0.50W	diode zener 15V
D0304	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0305	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0306	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0307	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0308	307916	DIODZ BZX 55C 7V5 0.50W	diode zener 7V5
D0309	307916	DIODZ BZX 55C 7V5 0.50W	diode zener 7V5
D0310	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0312	301254	DIODE 1N 4148 AXIAL	diode 1N 4148

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
D0314	328769	DIODE MR 752	diode MR 752
D0315	328769	DIODE MR 752	diode MR 752
D0316	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0317	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0319	329511	DIODZ BZX 55C 2V4 0.50W	diode zener 2V4
E0001	354859	RELAIS	relay 24V
E0301	354859	RELAIS	relay 24V
H0001	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k Ohm
H0301	343457	DICKS-NETZW. 8PIN 2%	res.network 8x10k Ohm
I0001	338359	IC LM 308 AN	IC LM 308 A
I0002	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP
I0003	327197	IC NE 5532 P 2FACH OP	IC NE 5532 N
I0004	307421	IC CA 3080 E OTA	IC CA 3080 E
I0005	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP
I0301	338359	IC LM 308 AN	IC LM 308 A
I0302	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP
I0304	307421	IC CA 3080 E OTA	IC CA 3080 E
I0305	331340	IC TL 072 CP 2FACH OP	IC TL 072 CP
J0001	336090	STIFTLEISTE 2POL STL11S-1	connector male 2-pin
J0002	336090	STIFTLEISTE 2POL STL11S-1	connector male 2-pin
L0001	348592	FILTERSP. 2.50UH/0.004OHM	coil 2.5uH
L0301	348592	FILTERSP. 2.50UH/0.004OHM	coil 2.5uH
Q0001	330264	TRANS J 111	transistor J 111 A
Q0002	335763	TRANS 2N 3904	transistor 2N 3904
Q0003	348421	TRANS 2N 3906	transistor 2N 3906
Q0004	335763	TRANS 2N 3904	transistor 2N 3904
Q0005	348421	TRANS 2N 3906	transistor 2N 3906
Q0006	335763	TRANS 2N 3904	transistor 2N 3904
Q0007	348421	TRANS 2N 3906	transistor 2N 3906
Q0008	348422	TRANS MPSA 42	transistor MPSA 42
Q0009	348423	TRANS MPSA 92	transistor MPSA 92
Q0010	348422	TRANS MPSA 42	transistor MPSA 42
Q0011	348423	TRANS MPSA 92	transistor MPSA 92
Q0012	348422	TRANS MPSA 42	transistor MPSA 42
Q0013	348423	TRANS MPSA 92	transistor MPSA 92
00010	348410	TRANS 2SB 1110 C	transistor 2SB 1110
00010	348411	TRANS 2SD 1610 C	transistor 2SD 1610
Q0016	348409	TRANS 2SC 4793	transistor 2SC 4793
Q0018	348421	TRANS 2N 3906	transistor 2N 3906
Q0019	335763	TRANS 2N 3904	transistor 2N 3904
Q0022	335763	TRANS 2N 3904	transistor 2N 3904
Q0023	348421	TRANS 2N 3906	transistor 2N 3906
Q0024	348409	TRANS 2SC 4793	transistor 2SC 4793
Q0025	348408	TRANS 2SA 1837	transistor 2SA 1837
Q0026	351981	TRANS MJL 3281 A	transistor MJL 3281 A
Q0027	351982	TRANS MJL 1302 A	transistor MJL 1302 A
Q0028	328889	TRANS MJ 15003	transistor MJ 15003
Q0029	328890	TRANS MJ 15004	transistor MJ 15004
Q0034	328889	TRANS MJ 15003	transistor MJ 15003
Q0035	328890	TRANS MJ 15004	transistor MJ 15004
Q0042	348422	TRANS MPSA 42	transistor MPSA 42
Q0043	348423	TRANS MPSA 92	transistor MPSA 92
Q0044	348423	TRANS MPSA 92	transistor MPSA 92

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
Q0045	348422	TRANS MPSA 42	transistor MPSA 42
Q0046	348423	TRANS MPSA 92	transistor MPSA 92
Q0047	348422	TRANS MPSA 42	transistor MPSA 42
00010	338876	TRIAC MAC 223 A6	triac MAC 223 A6
Q0051	348421	TRANS 2N 3906	transistor 2N 3906
Q0052	335763	TRANS 2N 3904	transistor 2N 3904
Q0053	348421	TRANS 2N 3906	transistor 2N 3906
Q0054	348421	TRANS 2N 3906	transistor 2N 3906
Q0055	335763	TRANS 2N 3904	transistor 2N 3904
Q0056	348423	TRANS MPSA 92	transistor MPSA 92
Q0057	348422	TRANS MPSA 42	transistor MPSA 42
Q0301	330264	TRANS J 111	transistor J 111 A
Q0302	335763	TRANS 2N 3904	transistor 2N 3904
Q0303	348421	TRANS 2N 3906	transistor 2N 3906
Q0304	335763	TRANS 2N 3904	transistor 2N 3904
Q0305	348421	TRANS 2N 3906	transistor 2N 3906
Q0306	335763	TRANS 2N 3904	transistor 2N 3904
Q0307	348421	TRANS 2N 3906	transistor 2N 3906
Q0308	348422	TRANS MPSA 42	transistor MPSA 42
Q0309	348423	TRANS MPSA 92	transistor MPSA 92
Q0310	348422	TRANS MPSA 42	transistor MPSA 42
Q0311	348423	TRANS MPSA 92	transistor MPSA 92
Q0312	348422	TRANS MPSA 42	transistor MPSA 42
Q0313	348423	TRANS MPSA 92	transistor MPSA 92
00010	348410	TRANS 2SB 1110 C	transistor 2SB 1110
00010	348411	TRANS 2SD 1610 C	transistor 2SD 1610
Q0316	348409	TRANS 2SC 4793	transistor 2SC 4793
Q0318	348421	TRANS 2N 3906	transistor 2N 3906
Q0319	335763	TRANS 2N 3904	transistor 2N 3904
Q0322	335763	TRANS 2N 3904	transistor 2N 3904
Q0323	348421	TRANS 2N 3906	transistor 2N 3906
Q0324	348409	TRANS 2SC 4793	transistor 2SC 4793
Q0325	348408	TRANS 2SA 1837	transistor 2SA 1837
Q0326	351981	TRANS MJL 3281 A	transistor MJL 3281 A
Q0327	351982	TRANS MJL 1302 A	transistor MJL 1302 A
Q0328	328889	TRANS MJ 15003	transistor MJ 15003
Q0329	328890	TRANS MJ 15004	transistor MJ 15004
Q0334	328889	TRANS MJ 15003	transistor MJ 15003
Q0335	328890	TRANS MJ 15004	transistor MJ 15004
Q0342	348422	TRANS MPSA 42	transistor MPSA 42
Q0343	348423	TRANS MPSA 92	transistor MPSA 92
Q0344	348423	TRANS MPSA 92	transistor MPSA 92
Q0345	348422	TRANS MPSA 42	transistor MPSA 42
Q0346	348423	TRANS MPSA 92	transistor MPSA 92
Q0347	348422	TRANS MPSA 42	transistor MPSA 42
00010	338876	TRIAC MAC 223 A6	triac MAC 223 A6
Q0351	348421	TRANS 2N 3906	transistor 2N 3906
Q0352	335763	TRANS 2N 3904	transistor 2N 3904
Q0353	348421	TRANS 2N 3906	transistor 2N 3906
Q0354	348421	TRANS 2N 3906	transistor 2N 3906
Q0355	335763	TRANS 2N 3904	transistor 2N 3904
Q0356	348422	TRANS MPSA 42	transistor MPSA 42
Q0357	348423	TRANS MPSA 92	transistor MPSA 92

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
R0086	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0087	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0106	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0107	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0131	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt
R0132	348590	WI-DR 8.20 OHM 4.00W 5%	resistor 8.20 Ohm 4watt
R0133	348590	WI-DR 8.20 OHM 4.00W 5%	resistor 8.20 Ohm 4watt
R0138	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0139	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0229	302032	WI-SCH 470.00 OHM 2.00W 5%	resistor 470 Ohm 2watt
R0231	302032	WI-SCH 470.00 OHM 2.00W 5%	resistor 470 Ohm 2watt
00005	348490	WI-SO NTC K 164/100K/J	safety component NTC
R0386	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0387	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0406	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0407	348456	WI-DR 2X 0.22 OHM 5.00W 5%	resistor 2x0.22 Ohm 5watt
R0431	341713	WI-DR 4.70 OHM 4.00W 5%	resistor 4.70 Ohm 4watt
R0432	348590	WI-DR 8.20 OHM 4.00W 5%	resistor 8.20 Ohm 4watt
R0433	348590	WI-DR 8.20 OHM 4.00W 5%	resistor 8.20 Ohm 4watt
R0438	348593	WI-SO NTC K 164/2.2K	safety component NTC
R0439	348593	WI-SO NTC K 164/2.2K	safety component NTC
T0001	336090	STIFTLEISTE 2POL STL11S-1	connector male 2-pin
T0301	336090	STIFTLEISTE 2POL STL11S-1	connector male 2-pin
VR001	348486	WI-TRI 47.00 KOHM LIN	pot trim 47k Ohm lin
VR002	348675	WI-TRI 2.50 KOHM LIN	pot trim 2.5k Ohm lin
VR301	348486	WI-TRI 47.00 KOHM LIN	pot trim 47k Ohm lin
VR302	348675	WI-TRI 2.50 KOHM LIN	pot trim 2.5k Ohm lin

	852378	PCB+A:L300/500/P550/600	PCB assy 85237
A	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
B	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
C	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN002	344862	MESSERLST. 8POL	connector male 8-pin
CN003	344862	MESSERLST. 8POL	connector male 8-pin
CN004	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin
CN006	348334	STIFTLEISTE 3POL MLSS	connector male 3-pin
CN007	343516	FL.STECKER 4.8/0.5	connector 4.8mm faston
CN008	343516	FL.STECKER 4.8/0.5	connector 4.8mm faston
CN009	343516	FL.STECKER 4.8/0.5	connector 4.8mm faston
C0001	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
C0002	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
C0003	327366	KO-EL 4.700MF 50V BIP	cap bip electr. 4.7uF/50V
C0051	335935	KO-EL 2200.000MF 35V	cap electrolytic 2200uF/35V
C0052	335935	KO-EL 2200.000MF 35V	cap electrolytic 2200uF/35V
C0055	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V
C0056	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V
C0057	342361	KO-KER 47.0PF K 100V 2%	cap ceramic 47pF
C0058	342361	KO-KER 47.0PF K 100V 2%	cap ceramic 47pF
C0059	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V
C0060	301472	KO-EL 10.000MF 63V	cap electrolytic 10uF/63V
C0068	342923	KO-FOL 0.220MF 63V 5%	cap mylar 220nF
C0069	342967	KO-FOL 3.300MF 50V 10%	cap mylar 3.3uF
C0071	340988	KO-FOL 0.470MF 63V 5%	cap mylar 470nF

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
C0072	343530	KO-EL 47.000MF 50V	cap electrolytic 47uF/50V
C0074	329021	KO-KER 0.10MF 100V 20%	cap ceramic 100nF
D0020	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8
D0021	304992	DIODZ BZX 55C 6V8 0.50W	diode zener 6V8
D0022	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0023	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0028	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0029	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0030	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0031	304360	DIODE 1N 4007 GEGURTET	diode 1N 4002
D0032	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0034	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0035	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0036	301254	DIODE 1N 4148 AXIAL	diode 1N 4148
D0037	331421	DIODZ BZT 03C 15V 3.50W	diode BZT 03C 15
D0038	331421	DIODZ BZT 03C 15V 3.50W	diode BZT 03C 15
E0001	356594	RELAIS 793-P-1A-S-TV10	relay 24V / spst
F0001	306838	SICHER-HALTER FAP	fuse holder
F0002	306838	SICHER-HALTER FAP	fuse holder
F0003	328390	SICHER-HALTER FAU	fuse holder
G0001	331965	GLRI B 80 C1500 G	rectifier B80 C1500
I0006	332985	IC TL 074 CN	IC TL 074 CN
M-E	343516	FL.STECKER 4.8/0.5	connector 4.8mm faston
M-L	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
M-N	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
M1	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
M2	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
Q0060	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0061	307430	TRANS BC 327-25 TO 92	transistor BC 327-25
Q0062	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0063	307430	TRANS BC 327-25 TO 92	transistor BC 327-25
00010	301236	TRANS BD 241 B	transistor BD 241 B
00010	301235	TRANS BD 242 B	transistor BD 242 B
Q0066	306928	TRANS BC 560 C	transistor BC 560 C
Q0067	306928	TRANS BC 560 C	transistor BC 560 C
Q0068	301184	TRANS BC 550 C	transistor BC 550 B
Q0069	306928	TRANS BC 560 C	transistor BC 560 C
Q0070	306928	TRANS BC 560 C	transistor BC 560 C
Q0071	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0072	307150	TRANS BC 337-25 TO 92	transistor BC 337-25
Q0073	301184	TRANS BC 550 C	transistor BC 550 B
Q0075	348591	TRANS BC 618 DARL. TO 92	transistor BC 618
Q0076	348591	TRANS BC 618 DARL. TO 92	transistor BC 618
Q0077	348591	TRANS BC 618 DARL. TO 92	transistor BC 618
Q0078	306928	TRANS BC 560 C	transistor BC 560 C
Q0082	306928	TRANS BC 560 C	transistor BC 560 C
Q0083	306928	TRANS BC 560 C	transistor BC 560 C
R0001	348550	WI-SO NTC 10 OHM K	safety resistor 10 Ohm
R0200	301726	WI-DR 22.00 OHM 5.00W10%	resistor 22 Ohm 5watt
R0201	301726	WI-DR 22.00 OHM 5.00W10%	resistor 22 Ohm 5watt
R0263	328799	WI-SCH 100.00 OHM 2.00W 5%	resistor 100 Ohm 2watt
R0264	328799	WI-SCH 100.00 OHM 2.00W 5%	resistor 100 Ohm 2watt
R0265	328799	WI-SCH 100.00 OHM 2.00W 5%	resistor 100 Ohm 2watt

Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Description
R0266	328069	WI-SCH 220.00 OHM 2.00W 5%	resistor 220 Ohm 2watt
S0001	338886	SCHALTER-SCHIEBE L202-02-1-	switch slide
S0302	327947	SCHALTELEMENT C42315-A1347-	switch element on/off
	302565	SICHER T 10.000 A/250V	fuse 10A slow blow
	328391	SICHER-HALTER-KAPPE FEK	fuse holder carrier
	302582	SICHER T 1.000 A/250V	fuse 1A slow blow
	852368	PCB+B.L300/500/P550/600/P-M	PCB assy 85236
CN001	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN002	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN003	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN004	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN005	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN006	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
CN007	330269	FL.STECKER 6.3/0.8	connector 6.3mm faston
C0001	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
C0002	348457	KO-EL 6800.000MF 80V 20%	cap electrolytic 6800mF/80V
C0003	348457	KO-EL 6800.000MF 80V 20%	cap electrolytic 6800mF/80V
C0004	348457	KO-EL 6800.000MF 80V 20%	cap electrolytic 6800mF/80V
C0005	348457	KO-EL 6800.000MF 80V 20%	cap electrolytic 6800mF/80V
C0006	341714	KO-SO 0.10MF 275V 20% K	safety cap 100nF/275V
G0001	348714	GLRI GBPC 3504 W WIRE LEADS	rectifier GBPC-W 3504