

		Ersatzteilliste - Bill of Materials		
	112728	ALPHA V-1/60		
	112729	ALPHA V-1/90		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
		Lautsprecherbestückung		Woofers & drivers
LA 01	361142	LA DL 15 Y	1	woofer DL 15Y
	454399	LA REP-KIT DL 15Y		recone kit DL 15Y
LA 02	360094	LA TREIBER DH 7	1	driver dh7
	452459	REPL.-KIT ND5-8		replacement diaphragm
LA 03	355354	LA HORN HP 64 S	1	horn HP64S
LA 03	355355	LA HORN HP 94 S	1	horn HP94S
LA 04	337755	LA HORN 2405 HPL SCHLITZ.	1	HF Transducer 2405H
	350100	MEMBRANE D16R2405		replacement diaphragm
LA 05	361543	LA ADAPTER ADH-6	1	adapter adh-6
		Gehäusematerial		Cabinet material
	356408	SCHUTZG. ALPHA V-1/60+90	1	grille
	302735	DICHTG-SEGM LA 15"	4	gasket 15"
	356412	A.F.ALPHA V-1/90	1	input panel S/A V-1/90
	356411	A.F.ALPHA V-1/60	1	input panel S/A V-1/60
B001	351652	BUCHSE-SPEAKON-RUND 8POL	1	socket 8pol SPEAKON
B002	351652	BUCHSE-SPEAKON-RUND 8POL	1	socket 8pol SPEAKON
S001	335941	SCHALTER-SCHIEBE 2XUM	1	switch slide
S002	335941	SCHALTER-SCHIEBE 2XUM	1	switch slide
	356410	BLEND.ALPHA V-1/90 BED	1	input panel -90
	356409	BLEND.ALPHA V-1/60 BED	1	input panel -60
	355848	GEH.ALP.V1-60/90	1	enclosure V1-60/90
		Frequenzweiche		X-over
	882578	PCB-H.V-1/60	1	pcb assy 88257 x-over
S001	336412	SCHALTER-SCHUTZ 3,15A	1	switch protection 3,15A
V001	344999	LAMPE-HALOGEN GESCHWEIßT	1	protection bulb
V002	344999	LAMPE-HALOGEN GESCHWEIßT	1	protection bulb
	336407	FL.STECKER A 4-6.3/0.8	4	connector 4-6.3mm faston
	882588	PCB-H.V-1/60 MID	1	pcb assy 88258 x-over
C001	304813	KO-FOL 6.800MF 100V 5%	1	cap mylar 6.8uF/100V
C002	330655	KO-FOL 1.000MF 100V 5%	1	cap mylar 1uF/100V
L001	356927	FILTERSP. 226.00UH/ 0.11OHM	1	inductor 226 uH
R004	336408	WI-DR 10.00 OHM20.00W 5%	1	resistor 10 Ohm/20watt
R005	336408	WI-DR 10.00 OHM20.00W 5%	1	resistor 10 Ohm/20watt
R006	336408	WI-DR 10.00 OHM20.00W 5%	1	resistor 10 Ohm/20watt
R007	337631	WI-DR 8.20 OHM20.00W10%	1	resistor 8.2 Ohm/20watt
R008	337631	WI-DR 8.20 OHM20.00W10%	1	resistor 8.2 Ohm/20watt
R009	337631	WI-DR 8.20 OHM20.00W10%	1	resistor 8.2 Ohm/20watt
R010	336403	WI-DR 27.00 OHM20.00W 5%	1	resistor 27 Ohm/20watt
R011	336403	WI-DR 27.00 OHM20.00W 5%	1	resistor 27 Ohm/20watt
R012	336403	WI-DR 27.00 OHM20.00W 5%	1	resistor 27 Ohm/20watt
	336407	FL.STECKER A 4-6.3/0.8	4	connector 4-6.3mm faston

	112728	ALPHA V-1/60		
	112729	ALPHA V-1/90		
Pos. Nr. Ref. No.	Best. Nr. Part No.	Bezeichnung	Qty	Description
	882598	PCB-H.V-1/60 HI	1	pcb assy 88259 x-over
C001	301405	KO-FOL 0.470MF 100V 5%	1	cap mylar 0.47uF/100V
C002	330655	KO-FOL 1.000MF 100V 5%	1	cap mylar 1uF/100V
C003	327199	KO-FOL 3.300MF 250V 5%	1	cap mylar 3.3uF/250V
C004	330178	KO-FOL 1.500MF 100V 5%	1	cap mylar 1.5uF/100V
L001	330176	FILTERSP. 106.00UH/ 0.16OHM	1	inductor 106 uH
V001	344999	LAMPE-HALOGEN GESCHWEIßT	1	protection bulb
	330269	FL.STECKER 6.3/0.8	3	connector 6.3mm faston
	336407	FL.STECKER A 4-6.3/0.8	4	connector 4-6.3mm faston
		Verpackung & Zubehör		Packaging material & Accessories
	356424	KRT. ALPHA V-1/60+90	1	carton
	357576	FALTEINL. ALPHA V-1/60+90	2	carton filler
	345156	SCHUTZHÜLLE 1160X1200X0,08	1	poly bag
	356353	PALETTE EW 600X800	1	pallet
	344439	SCHUTZHÜLLE 750X850X0,08	1	poly bag
	357572	DAT.BLATT/EDS ALPHA V-1/90	1	EDS
	356428	DAT.BLATT/EDS ALPHA V-1/60	1	EDS
	353359	BEZ.SCHILD ALPHA	1	logo ALPHA
	345119	FITTING DOUBLE-STUD	3	rig fitting double stud
	351651	STECKER-SPEAKON 8POL	1	connector SPEAKON 8-pol